

Betrieb von LED-Retrofit Lampen LED Star RaLEDina mit verschiedenen Dimmern



Legende:

green	dimmbability very good (under 25% light)
yellow	dimmmable (under 40% light)
red	dimmbability critical (flickering and/or sound possible, and/or only more than 40% light)
white	not tested



T: Trailing edge phase dimmer
 L: Leading edge phase dimmer
 U: Universal dimmer

Manufacturer	Dimmer-Type, Model	Mains/Power	Load Range [W]	Dimming Method	RAL35 43514840 43514838			RAL60 43514841 43514839			RAL120 42614837		
					1 Lamp	2 Lamps	3 Lamps	1 Lamp	2 Lamps	3 Lamps	1 Lamp	2 Lamps	3 Lamps
ABB	STD 50-3	230/50Hz	60-500	L	99-0%	99-0%	99-0%	99-0%	99-0%	100-0%	98-0%	98-0%	98-0%
Altenburger	50.3	230/50Hz						99-0%	98-0%	99-0%		97-0%	97-0%
AURORA	DSP 400	230/50Hz	400	L	99-0%	99-0%	100-0%	99-0%	99-0%	100-0%	99-0%	98-0%	99-0%
Berker	2861	230/50Hz	50-420	U	100-0%	100-0%	100-0%	87-0%	97-0%	99-0%	82-0%	99-0%	99-0%
Bticino	L/N/NT4411NHC/HD/HS4411	230/50Hz			99-0%	99-0%	99-0%	99-0%	98-0%	99-0%	94-0%	98-0%	98-0%
blicino	NT4402N	230/50Hz	500	R				99-0%	99-0%	99-0%	98-0%	99-0%	100-0%
Busch-Jaeger	6513 U-102	230/50Hz	420	T	100-0%	100-0%	100-0%	99-0%	99-0%	99-0%	100-0%	99-0%	99-0%
Busch-Jaeger	6523 U-102	230/50Hz	40-420	T	100-0%	100-0%	100-0%	99-0%	99-0%	99-0%	100-0%	100-0%	99-0%
Busch-Jaeger	2250 U	230/50Hz	60-600	L				99-0%	99-0%	99-0%	99-0%	99-0%	98-0%
Busch-Jaeger	6526 U	230/50Hz			100-0%	99-0%	100-0%	100-0%	100-0%	100-0%	100-0%	99-0%	98-0%
CENTURY CONTROL	MULTI DIMMER	230/50Hz	60-600	U	98-0%	99-0%	99-0%	99-0%	99-0%	99-0%	98-0%	99-0%	99-0%
DINUY	RE EL1 LE1	230/50Hz	400	LED	99-0%	99-0%	99-0%	98-0%	98-0%	99-0%	98-0%	98-0%	99-0%
ELKO	400GLI	230/50Hz						99-0%	99-0%	99-0%	99-0%	99-0%	98-0%
ELKO	315GLE	230/50Hz	20-315	T	80-0%	100-0%	100-0%	96-0%	99-0%	100-0%	100-0%	99-0%	99-0%
ELKO	600GLE/I	230/50Hz			100-0%	99-0%	99-0%	99-0%	100-0%	99-0%	99-0%	99-0%	99-0%
ELKO	600GLI	230/50Hz	40-600	U	99-0%	99-0%	99-0%	99-0%	100-0%	99-0%	99-0%	98-0%	98-0%
ELKO	420GLE/I	230/50Hz	40-420	U	99-0%	99-0%	99-0%	99-0%	100-0%	100-0%	99-0%	99-0%	99-0%
ELKO	1000RLI	230/50Hz			98-0%	99-0%	99-0%	98-0%	99-0%	99-0%	98-0%	99-0%	99-0%
ELKO	630GLE	230/50Hz	20-630	U		100-0%	100-0%	86-0%	100-0%	100-0%	92-0%	100-0%	99-0%
Eltako	EUD61NPN-UC	230/50Hz	5-400	R / L / C	100-0%	100-0%	100-0%	99-0%	99-0%	100-0%	99-0%	100-0%	100-0%
Feller	40200.LEDxxx	230/50Hz			100-0%	100-0%	100-0%	97-0%	100-0%	99-0%	100-0%	99-0%	99-0%
Feller	40600.RLC	230/50Hz	20-600	U	100-0%	99-0%	99-0%	99-0%	100-0%	99-0%	99-0%	99-0%	99-0%
Feller	40600.RC	230/50Hz				100-0%	100-0%	86-0%	100-0%	100-0%	92-0%	100-0%	99-0%
Feller	40600.RL	230/50Hz			99-0%	99-0%	99-0%	99-0%	100-0%	99-0%	99-0%	98-0%	98-0%
Feller	40420.RLC	230/50Hz			99-0%	99-0%	99-0%	99-0%	100-0%	100-0%	99-0%	99-0%	99-0%
Feller	31000	230/50Hz			97-0%	98-0%	100-0%	98-0%	99-0%	99-0%	98-0%	98-0%	99-0%
GIRA	226200	230/50Hz						99-0%	99-0%	99-0%	99-0%	98-0%	98-0%
Gira	030700	230/50Hz	20-525	T	100-0%	100-0%	100-0%	98-0%	97-0%	98-0%	99-0%	100-0%	99-0%
Gira	117600	230/50Hz	50-420	U	93-0%	100-0%	99-0%	87-0%	97-0%	99-0%	87-0%	99-0%	99-0%
Gira	238500	230/50Hz			76-0%	96-0%	100-0%	91-0%	96-0%	100-0%	94-0%	99-0%	99-0%
Gira	217400	230/50Hz	4X20-250	KNX-U	99-0%	100-0%	99-0%	99-0%	98-0%	99-0%	99-0%	100-0%	100-0%
Hager	WUD87	230/50Hz	400	LED-U	94-0%	91-0%	100-0%				89-0%	88-0%	88-0%
Hamilton	KP1X40	230/50Hz	400		100-0%	100-0%	100-0%	100-0%	99-0%	100-0%	99-0%	99-0%	98-0%
Hugo Müller	paladin 872110 led	230/50Hz			99-0%	99-0%	99-0%	98-0%	98-0%	99-0%	98-0%	98-0%	99-0%
Jung	225 NVDE	230/50Hz	20-500	L				99-0%	99-0%	99-0%	99-0%	98-0%	98-0%
Jung	225 TDE	230/50Hz			100-0%	100-0%	100-0%	98-0%	97-0%	98-0%	99-0%	100-0%	99-0%
Jung	254 UDIE1	230/50Hz			93-0%	100-0%	99-0%	87-0%	97-0%	99-0%	87-0%	99-0%	99-0%
Jung	1224 LEDUDE	230/50Hz		LED	76-0%	96-0%	100-0%	91-0%	96-0%	100-0%	94-0%	99-0%	99-0%
Jung	3904 REGHE	230/50Hz			99-0%	100-0%	99-0%	99-0%	98-0%	99-0%	99-0%	99-0%	100-0%
Legrand	665114	230/50Hz	400	U	99-0%	99-0%	99-0%	99-0%	98-0%	99-0%	94-0%	98-0%	98-0%
Legrand	574319/574339	230/50Hz	400	U	99-0%	99-0%	99-0%	99-0%	98-0%	99-0%	94-0%	98-0%	98-0%
Legrand	572239/572739	230/50Hz	400	U	99-0%	99-0%	99-0%	99-0%	98-0%	99-0%	94-0%	98-0%	98-0%
Legrand	078407/079207	230/50Hz	400	U	99-0%	99-0%	99-0%	99-0%	98-0%	99-0%	94-0%	98-0%	98-0%
Legrand	048869/048871	230/50Hz	400	U	99-0%	99-0%	99-0%	99-0%	98-0%	99-0%	94-0%	98-0%	98-0%
Legrand	067083/048869	230/50Hz	400	U	99-0%	99-0%	99-0%	99-0%	98-0%	99-0%	94-0%	98-0%	98-0%
Legrand	099314	230/50Hz	300	RL	98-0%	99-0%	99-0%	99-0%	99-0%	99-0%	98-0%	98-0%	98-0%
Legrand	770062	230/50Hz	400	RLC	99-0%	99-0%	99-0%	98-0%	97-0%	98-0%	98-0%	98-0%	98-0%
MASTER	DM-DGL	230/50Hz	1000	U / LED	93-0%	95-0%	93-0%	93-0%	99-0%	99-0%	98-0%	99-0%	100-0%
MASTER	DM-2500	230/50Hz	2500	U / LED	97-0%	99-0%	97-0%	99-0%		99-0%		99-0%	100-0%
Merten	MEG5136-0000	230/50Hz			80-0%	100-0%	100-0%	96-0%	99-0%	100-0%	100-0%	99-0%	99-0%
Merten	MEG5134-0000	230/50Hz			100-0%	100-0%	100-0%	97-0%	100-0%	99-0%	100-0%	99-0%	99-0%
Merten	MEG5139-0000	230/50Hz			100-0%	99-0%	99-0%	99-0%	100-0%	99-0%	99-0%	99-0%	99-0%
Merten	MEG5137-0000	230/50Hz				100-0%	100-0%	86-0%	100-0%	100-0%	92-0%	100-0%	99-0%
Merten	MEG5133-0000	230/50Hz			99-0%	99-0%	99-0%	99-0%	100-0%	99-0%	99-0%	98-0%	98-0%
Merten	MEG5138-0000	230/50Hz			99-0%	99-0%	99-0%	99-0%	100-0%	100-0%	99-0%	99-0%	99-0%
Merten	MEG 5170-0300	230/50Hz	10-200	U	57-0%	55-0%	56-0%	50-0%	51-0%	51-0%	51-0%	51-0%	51-0%
Merten	MEG 5131	230/50Hz	40-400	L	99-0%	99-0%	99-0%	99-0%	100-0%	100-0%	99-0%	99-0%	98-0%
Merten	MEG 5132	230/50Hz			99-0%	99-0%	99-0%	99-0%	100-0%	100-0%	99-0%	99-0%	98-0%
Merten	MEG5140	230/50Hz	9-100	L	100-0%	99-0%	100-0%	99-0%	100-0%	100-0%	99-0%	98-0%	97-0%
Merten	MEG 5135	230/50Hz	60-1000	L	98-0%	99-0%	99-0%	98-0%	99-0%	99-0%	98-0%	99-0%	99-0%
MK	K4501	230/50Hz	180	L	100-0%	100-0%	100-0%	99-0%	99-0%	99-0%	99-0%	99-0%	98-0%
NEXJUS	881P-01	230/50Hz	400	L	99-0%	99-0%	100-0%	99-0%	99-0%	99-0%	98-0%	98-0%	99-0%
NIKO	310-0190001901	230/50Hz	5-200	U	100-0%	100-0%	100-0%	99-0%	100-0%	99-0%	99-0%	100-0%	100-0%
NIKO	330-0070000701	230/50Hz	5-200	U	99-0%	100-0%	100-0%	99-0%	99-0%	100-0%	100-0%	100-0%	100-0%
Odace	S520512	230/50Hz			100-0%	100-0%	100-0%	97-0%	100-0%	99-0%	100-0%	99-0%	99-0%
Odace	S520511	230/50Hz			99-0%	99-0%	99-0%	99-0%	100-0%	99-0%	99-0%	98-0%	98-0%
Odace	S520515	230/50Hz			99-0%	99-0%	99-0%	99-0%	100-0%	100-0%	99-0%	99-0%	99-0%
Osram	HTI DALI 315 DIM	230/50Hz	20-315	DALI-T	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	99-0%	100-0%
PEHA	435 HAN	230/50Hz	60-600	L	97-0%	99-0%	100-0%	102-0%	100-0%	100-0%	99-0%	98-0%	98-0%
Schneider	400GLI	230/50Hz	40-400	T			99-0%	99-0%	99-0%	99-0%	99-0%	99-0%	98-0%
Schneider	SBD315RC	230/50Hz			80-0%	100-0%	100-0%	96-0%	99-0%	100-0%	100-0%	99-0%	99-0%
Schneider	SBD200LED	230/50Hz	400		100-0%	100-0%	100-0%	97-0%	100-0%	99-0%	100-0%	99-0%	99-0%
Schneider	SBD600RCRL	230/50Hz			100-0%	99-0%	99-0%	99-0%	100-0%	99-0%	99-0%	99-0%	99-0%
Schneider	SBD630RC	230/50Hz				100-0%	100-0%	86-0%	100-0%	100-0%	92-0%	100-0%	99-0%
Schneider	SBD600RL	230/50Hz			99-0%	99-0%	99-0%	99-0%	100-0%	99-0%	99-0%	98-0%	98-0%
Schneider	SBD420RCRL	230/50Hz			99-0%	99-0%	99-0%	99-0%	100-0%	100-0%	99-0%	99-0%	99-0%
Schneider	5170	230/50Hz			57-0%	55-0%	56-0%	50-0%	51-0%	51-0%	51-0%	51-0%	51-0%
Schneider	SBD400RL	230/50Hz			99-0%	99-0%	99-0%	99-0%	100-0%	100-0%	99-0%	99-0%	98-0%
Schneider	ATD1000RL	230/50Hz			98-0%	99-0%	99-0%	98-0%	99-0%	99-0%	98-0%	99-0%	99-0%
Shuttle	SDIM-T-LED-500W	230/50Hz	2-500	T & LED-T	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%		99-0%	99-0%
Siemens	5TC8 284	230/50Hz	20-525	T	89-0%	96-0%	98-0%	81-0%	85-0%	88-0%	83-0%	91-0%	93-0%
Siemens	5WG1-528-1AB31	230/50Hz	20-500	KNX-U	99-0%	100-0%	99-0%	99-0%	99-0%	99-0%	100-0%	99-0%	100-0%
VADSBO	LD 220	230/50Hz	1-200	U	98-0%	99-0%	99-0%	99-0%	98-0%	99-0%	98-0%	98-0%	98-0%
VARILIGHT	HQ3W	230/50Hz	400		96-0%	98-0%	98-0%	95-0%	98-0%	98-0%	97-0%	97-0%	98-0%
VARILIGHT	JOP401W	230/50Hz	400	T		99-0%	100-0%	84-0%	100-0%	100-0%	99-0%	98-0%	99-0%
Vimar	20135	230/50Hz	3-100	U	100-0%	100-0%	100-0%	99-0%	99-0%	99-0%	99-0%	100-0%	100-0%
ZANO	WH401	230/50Hz	400	L		99-0%	100-0%	100-0%	99-0%	100-0%	99-0%	99-0%	99-0%
ZANO	WH251	230/50Hz	250										

Betrieb von LED-Retrofit Lampen LED Star RaLEDina mit verschiedenen Dimmern



Legende:

green	dimmbility very good (under 25% light)
yellow	dimmbable (under 40% light)
red	dimmbility critical (flickering and/or sound possible, and/or only more than 40% light)
white	not tested

T: Trailing edge phase dimmer
 L: Leading edge phase dimmer
 U: Universal dimmer

RAL35		RAL60			RAL120		
	43514840		43514841			42614837	
	43514838		43514839				

Manufacturer	Dimmer-Type, Model	Mains/Power	Load Range [W]	Dimming Method	1 Lamp	2 Lamps	3 Lamps	1 Lamp	2 Lamps	3 Lamps	1 Lamp	2 Lamps	3 Lamps

when using other LED-lamp types.

Due to the big number of electronic components and many other influence factors noise can emerge in unfavourable condiditons, which may be well audible in the case of resonance.

Generally speaking, employment of trailing edge dimmers is recommended. They require the neutral wire for installation.

Changes, errors and omissions excepted.